

# HID-PV C 2x70 /S CDM



Philips Lighting Electronics  
GDC Eindhoven  
Author: Johan Kokx  
March 2011

9137-006-41866 sh-460 2011-03-28

HID-PV C 2x70 /S CDM

9137-006-41866 sh-460 2011-03-28

# HID-PV C 2x70 /S CDM

## Contents

1. Introduction	3
2. Version management	3
3. Ordering	3
4. Dimensions and mechanical design-in	3
5. Temperature behaviour	3
6. Wiring	4
7. Electro-Magnetic Compatibility	5
8. Factory handling	5
9. Installation / Mounting	6
10. Operating in abnormal conditions	7
11. Advised communication	7
12. Frequently Asked Questions	8
13. For more information	8

HID-PV C 2x70 /S CDM

9137-006-41866 sh-460 2011-03-28

# HID-PV C 2x70 /S CDM

## 1. Introduction

The PrimaVision Compact Twin 70W allows use of two lamps with the same driver. The driver has been renewed and improved and now fulfils to CISPR 15 ed 7.2. The new driver has the same footprint as its predecessor to allow easy design-in.

## 2. Version management

This is the design-in sheet for the PrimaVision Compact 70W /S driver.

Status of the product: Final

Previous status: -

**28-03-2011:** 9137-006-418 sht-460 2011-03-28

Initial document

## 3. Ordering

Technical name: HID-PV C 2x70 /S CDM

12NC: 9137 006 41866

EAN3: 8727900845792

EOC: 872790084579200


Product	Qty box/pallet	Net weight (kg)	Box Dim. LxWxH (mm)	Pallet Dim. LxWxH (mm)
HID-PV C 2x70 /S CDM	12/576	0.46	390x250x114	1200x1000x620

## 4. Dimensions and mechanical design-in

### Mechanical design-in

This driver should be fixed with the bottom of the mounting-plate onto the housing of the luminaire. It should be mounted by means of 2 screws (M4).

### Dimensions




A1 (mm)	A2	B1 (mm)	B2 (mm)	C1 (mm)	D1 (mm)
165.0	153.0	90	80.0	32.0	4.5

## 5. Temperature behaviour

### T<sub>case</sub>

The T<sub>case</sub>-point is the position shown on the drawing below. The thermo-couple should be mounted on the metal bracket.

# HID-PV C 2x70 /S CDM



Lifetime 40k hours/90% survivals:

	$T_{case-max}$	$T_{ambient-max}$
HID-PV C 2x70 /S CDM	80°C	50

## Driver losses

The PrimaVision Compact TWIN drivers have been developed to realize high power efficiency and operate with low losses for a long reliable lifetime.

Please note that it is necessary for the PrimaVision Compact driver to establish a **good** thermal contact between the driver chassis (bottom plate) and the luminaire chassis in order to achieve sufficient cooling of the driver and prolonged driver lifetime. There should be no air gap present between the driver chassis and the luminaire surface. Do not exceed  $T_{case-max}$ .

## Temperature Testing


Because the driver will regulate the lamp to a constant power, the input current will increase when the input voltage is lower. This ultimately will influence the power losses, so the worst-case temperature should therefore be measured at lowest mains voltage of 198V.

To guarantee, that the maximum value of  $T_{case}$  is not exceeded, a thermo-couple should be mounted on the  $T_c$  point of the driver.


For more information about lifetime and temperature please consult the HID application guide.

## 6. Wiring

The wiring should be connected according the picture below. This driver is equipped with a safety earth connection and must be connected to the earth connection of the mains-supply.

For EMI-reasons, it is important to make the “hot” lamp-wires (indicated by the ) as short as possible

# HID-PV C 2x70 /S CDM



Connector type:	Push-in contacts, WAGO type 804
Wire cross section:	0.75..2.5 mm <sup>2</sup> massive or stranded
Strip length	10-11 mm
Max cable capacitance lamp-wires:	100 pF
Maximum length lamp-wires:	1.5m

## 7. Electro-Magnetic Compatibility

The driver is tested and approved according CISPR 15 ed. 7.2.

However the position of the wiring can negatively influence the EMC behaviour of this HID-system. Therefore it is advised to pay attention to the following:

- Place the mains-wires in such a way, that they are not in parallel with the lamp-wires.
- Make the spacing between lamp- and mains-wires as big as possible.
- Keep the mains-wires close together.
- Keep the lamp-wires close together and preferably as short as possible. However do not exceed the maximum allowed length of the lamp-wires.


## 8. Factory handling

### Fixation in luminaire

Permanent force on components and connectors should be prevented. This stress may cause fatigue on the solder joints and may result in premature lifetime failures. This can be prevented by carefully selecting wires (flexible), luminaire construction (free spaces for wires) and the application of strain relieves.


### Traceability

For traceability reasons year and week of production, as well as production-location, can be found on the product-label and on the housing.



**PHILIPS**

# HID-PV C 2x70 /S CDM



The production-code consists of following info:



- CCC Factory Code
- YY Year
- WW Week
- D – Day
- Z – Production Sequence

## 9. Installation / Mounting

### Lamps that can be driven by the driver

Driver	Lamp
HID-PV C 2x70W /S	All CDM 70W lamps

The drivers are not compatible with the following lamps:

- Metal halide quartz lamps

### Suitable application for this driver

This product is designed mainly for luminaires that are working in an Indoor environment (IP23 or superior casing).

The PrimaVision Compact Twin range is not intended for Outdoor use due to the following outdoor constraints:

- High humidity and condensation risks
- Vibrations e.g. when the luminaire is mounted on a public lighting pole
- Lightning surges on the mains. Outdoor electronics driver are 4kV protected but the HID-PV C 2x 70W is protected up to 2kV.

Therefore, it is the responsibility of the luminaire manufacturer and the installer to take into account the above and implement adequate protection for the above. Here are some requirements for Outdoor applications:

- Place the driver in an IP54 or higher environment
- Avoid placing the driver or luminaire in high poles
- Place adequate Lightning protection in the lighting installation
- Planner should take it into account for Cost of Ownership calculations and maintenance plans.

# HID-PV C 2x70 /S CDM

If the above points are not taken into account in the design and the installation, Philips Lighting Electronics will have the option not to apply the standard guarantee.

## Maximum number of drivers per MCB

The maximum number of drivers, which can be connected to a MCB, can be found in the table below:

Driver type	Maximum number of drivers per MCB			
	B16A	B10A	C16A	C10A
HID-PV C 2x70W /S	10	6	17	10
Relative number of drivers	100%	63%	170%	104%

## DC-operation

This driver is not designed for DC-operation.

## 10. Operating in abnormal conditions

### Active Thermal protection

If the driver is used at a too high temperature an internal thermal protection will protect the driver against damage; the driver will switch off the lamp. Mains voltage needs to be reset in order to reset thermal protection.

The thermal protection becomes active at  $T_{case} > 100^{\circ}\text{C}$ .

### Mains voltage

The driver is designed to operate within a operational/safety range of 180-264V. However the performance is guaranteed within the performance range of 198-254V. Within this range, the lamp power is regulated within  $\pm 3\%$  of its nominal power. (Valid for a lamp-voltage between 80 and 90V)

### Lightning and power surges

Protection against surges because of lightning are built in the driver.  
IEC61547, surge levels: 1.0kV Line to Line and 2.0kV Line to GND

### End Of Life (EOL) lamp protection

The driver has a protection against an End Of Life Lamp. The driver will detect the failing lamp and switch off. After re-lamping, the mains has to be switched off and on, in order to reset the driver.

## 11. Advised communication

Philips Lighting Electronics advises to communicate the following information to your customers via your preferred media: Catalogues, brochures, Product datasheets, Mounting instructions, Internet and Intranet.

### Technical

Due to lamp characteristics, this driver needs some time to re-ignite (10...15 minutes) after switch off.

When the lamp has reached end of life, the driver will switch off the lamp in order to avoid lamp overheating. After lamp replacement, the mains voltage will have to be reset and the system will work normally. The driver does not need to be replaced. The PrimaVision Twin driver range is equipped with an internal thermo-

# HID-PV C 2x70 /S CDM

switch that will prevent loss of driver lifetime due to overheating in the luminaire/installation.

Check also chapter 9 for relevant technical information

## Marketing

The use of PrimaVision Compact Twin in your luminaire will provide your customer the following benefits:

- **Optimum system performance**  
Development of CDM lamps and driver is in one hand. Every product is tested extensively, requiring a million burning hours before a system can be released. The result is an optimal light performance with Philips MASTERColour CDM lamps.
- **Flicker free operation**
- **30 to 40% longer lamp lifetime**
- **10% energy saving compared to a Electromagnetic system**
- **Safe and comfortable behaviour when lamp reaches End of Life**

Furthermore, the PrimaVision Compact Twin range has low losses, which guarantees maximum energy savings and limit heat generation, translating into a longer driver lifetime.

## Guarantee

The guarantee of 3 and 5 years for Philips Electronics is applicable for this product. For more information about guarantee, please visit our website:

[Http://www.lampsandgear.philips.com/](http://www.lampsandgear.philips.com/)

## 12. Frequently Asked Questions

### Can I use this driver in a 24hr-7days installation?

No, this driver is not suitable for 24/7 operation.

### What will happen if 1 lamp fails?

This will have no effect on the other lamp. They work fully independent. When one lamp is old, broken or not connected, the other lamp keeps functioning normally.

To replace the non-functioning lamp, switch off the mains, replace the non-functioning lamp by a new lamp and switch on the mains again.

## 13. For more information

Please contact your local sales representative.

Check OEM application guide for general information about electronic gear.

Visit our web-site [www.Philips.com/eHID](http://www.Philips.com/eHID)