


PHILIPS

CertaFlux

LED System



Design-in Guide

Philips CertaFlux HighBay Module


design in guide

March 2018

Contents

Introduction to this guide	3	Thermal design-in	11
Information and support	3	Optimum performance	11
Determine which documents contain what information	3	Operating temperature	11
		Thermal measurements	12
		Critical temperature point (Tcase)	12
		Measurement of critical temperature point	12
Warnings and instructions	4	Electrical design-in and flexibility	13
Safety warnings and installation instructions	4	Connection to the mains supply	13
Design-in phase	4	Philips outdoor driver	13
Manufacturing phase	5	Compatible Drivers with this module	13
Installation and service for luminaires	5		
Philips Design-in support	5		
Introduction to this module	6	Reliability	14
Applications and luminaire classification	6	Lumen maintenance	14
Luminaire Class I applications	6		
Commercial naming	6	Controllability	15
In this design-in guide	6	Dimmable function for the driver	15
Cautions during storage and transportation	6		
When storing this product for a long time (more than oneweek)		Compliance and approval	16
During transportation and storage for a short time	6	Compliance and approbation	16
Xitanium outdoor drivers for this module	7	IP rating, humidity and condensation	16
		Electrostatic discharge (ESD)	16
		Blue Light Hazard	17
		Chemical Compatibility	18
		Cautions	18
Optical design-in	8	Contact details	19
Light distribution	8	Disclaimer	20
Color consistency	8		
Color targets	8		
Spectral light distribution	8		
Mechanical design-in	10		
About CertaFlux High Bay module	10		
Mechanical fixation	10		
Wiring	10		
Installation Guide	10		

Introduction to this guide



Thank you for choosing the Philips product. In this guide you will find the information required to design this module into a luminaire.

Information and support

If you require any further information or support, please consult your local Philips office or visit our website:

<http://www.lighting.philips.com.sg/oem-sg>

Determine which documents contain what information

In order to provide information in the best possible way, Philips' philosophy on product documentation is the following.

Commercial leaflet contains product family information & system combinations (compatible Philips driver information)


Datasheet contains the module (module and multi-connector) specification

Design-In Guide describes how to design-in the products

All these documents can be found on the download page of the OEM website

<http://www.lighting.philips.com.sg/oem-sg>

If you require any further information or support, please consult your local Philips office.



Download section of the OEM web

Warnings and instructions



Warnings:

- Metal enclosure of module must be grounded

Safety warnings and installation instructions

To be taken into account during design-in and manufacturing.

Design-in phase

- Do not apply mains power to the module directly.
- Connect the modules and drivers before switching on mains.
- Avoid contamination (direct or indirect) from any incompatible chemicals reacting with the LED. A list of incompatible chemicals is provided in the chapter for Compliance and Approval.
- The general IEC recommendations for luminaire design and legal safety regulations are also applicable to Philips module. Luminaire manufacturers are advised to conform to the international standards for luminaire design Class I, IEC 60598-Luminaires).
- Class I luminaires must provide a protective earth.
- The luminaire must be constructed in such a way that the LED module cannot be touched by an end-user, both in off state and when live.
- It is mandatory to design the luminaire in such a way that it can only be opened with special tools (by a qualified person) in order to prevent touching of live parts.
- Do take into account the minimum required creepage and clearance distances.
- Connect all electrical components first before switching on mains.
- The LED module shall be powered by a LED control gear IEC/EN 61347-2-13 certified.
- Module is not applicable for outdoor application (>IP65).
- Module is not applicable for Explosion-Risk application, such as gasoline station.

Manufacturing phase

- Do not use damaged or defective LED modules, including damaged connectors or PCB.
- Do not drop the LED module or let any object fall onto the LED module because this may damage the glass of the module. If the LED module has been dropped or an object has fallen onto the LED module, do not use it, even if there are no visible defects or signs of damage.
- Connect all electrical components first before switching on mains.
- The LED module shall be powered by a LED control gear IEC/EN 61347-2-13 certified.

Installation and service for luminaires incorporating with Philips module

- Do not service the luminaire when the mains voltage is connected; this includes connecting or disconnecting the LED module cables.
- Do not use damaged products.
- Module should always be replaced by an OEM-qualified installer.
- The water proof connector has to be fully tightened up to prevent the water penetration via the connection in the field application.
- Any luminaire design please refer to the Tc definition for Philips module, to avoid any potential risk happened.

Philips Design-in support

Is available; please contact your Philips sales representative.

Introduction to this module

Applications and luminaire classification

Philips CertaFlux Highbay module is an integrated module solution, excellent optical and heat management. The entire system set includes module, driver perfect for easy design-in for industrial applications. The portfolio has been defined to include color temperatures of 4000K and 5700K, lumen package of 10K, 15K, 20K lumen totally.

Luminaire Class I applications

The module are suitable for luminaire Class I applications in combination with approved Philips outdoor IP67 driver. Approved combinations comply with the latest IEC60598 luminaire standard requirements.

In this design-in guide


In this design-in guide you will find all necessary guidelines to configure the module to your needs. The module range is designed to enable all types of luminaires in industrial field. And it is capable of truly replacing all those conventional industrial luminaires

Cautions during storage and transportation When storing this product for a long time (more than oneweek)

- Store in a dark place. Do not expose to direct sunlight
- Please refer to the relevant product datasheet.

During transportation and storage for a short time

Maintain temperature below 65°C at normal, noncondensing relative humidity.



Xitanium outdoor drivers for this module

These LED outdoor drivers are available as an independent IP67 driver.


More information about the Xitanium drivers can be found in the Xitanium outdoor driver design in guide and commercial leaflet. These documents can be downloaded via

<http://www.lighting.philips.com.sg/oem-sg>


The Xitanium driver datasheets can also be downloaded on this website.

It is highly recommended to use the approved Philips Xitanium LED drivers. For a list of approved drivers please refer to www.easydesignintool.com


Optical design-in



Light distribution of the Certaflex High Bay Module



Certaflex high bay with reflector(60D)
Polar intensity diagram



Certaflex high bay with reflector(90D)
Polar intensity diagram

Light distribution

This module is suitable for industrial application. Optical files can be downloaded from <http://www.lighting.philips.com.sg/oem-sg>

The Reflector High bay xxxMM 60D/90D are products designed for OEMs looking for a "one stop shop", where module and reflector are provided by Philips allowing a short fixture development cycle, while enabling basic optical flexibility with its two standard light distributions.

Please check the datasheet and installation guide for detail.

For OEMs looking to have a unique photometrical performance, the interface of Certaflex High Bay module were designed to operate together with third party reflector, enabling an endless number of possible configurations.

Color consistency

Color consistency refers to the spread in color points between modules. It is specified in SDCM (Standard Deviation of Color Matching) or MacAdam ellipses, which are identical. You can find the SDCM data in the commercial datasheet for the current general specification of module. This results in good color consistency performance for industrial application.

Color targets

The color target points of modules are found in the respective datasheets on <http://www.lighting.philips.com.sg/oem-sg>

Spectral light distribution

The spectral light distribution of modules are found in the respective datasheets on <http://www.lighting.philips.com.sg/oem-sg>

Note:

Component and process tolerances can result in imperfectly symmetrical light distributions. Maximum acceptable tolerances will have minimal impact on optical distributions and optical performance in the final application for a variety of reasons.

All polar intensity diagram illustrations are just an indication of the beam shape. We suggest making use of the IES files available on the module website.

Mechanical design-in

About CertaFlux High Bay module

Do not open Certaflux High bay module during the mechanical Design-in as Certaflux High bay module is a highly integrated module.

The dimensions for the Certaflux High bay modules are provided in the respective datasheets. These, along with the CAD files can be downloaded from our website www.Philips.com/Technology.



Mechanical fixation

The selected driver is recommended to be installed on the top of the module, as indicated in the figure on the left. Please refer to the driver DIG for specific instructions regarding the installation of the driver. At least one mounting hole at each side of the driver should be used to fix it. Required screw is included in the product package. The recommended torque is 0.7 Nm.

The hole at the side of CertaFlux High Bay module is specially designed for installing safety cable. Safety cable/hook must be connected to prevent accidental falling. It is for safety purposes only and cannot be used for suspending the luminaire. Safety cable can be provided either through Philips (12NC of the safety cable is xxxxxxxxxxxx) or via the third party supplier. Please contact your local sales representative.


The bracket and ring screw on the module is used to hang CertaFlux High Bay for field application. For safety purposes, do not loosen or disassemble the bracket and ring screw.

Wiring

IP67 connector solution, more information please check datasheet. The water proof connector has to be fully tightened to prevent the water leaking into the connection in the field application. The recommended torque is 1.2N·m.

Installation Guide

Additional installation guide can be downloaded from our website www.lighting.philips.com.sg/oem-sg.



Safety cable



Connect safety cable with
CertaFlux high bay module

Thermal design-in

The critical thermal management points for the LED module are set out in this chapter in order to facilitate the design-in of this module. If these thermal points are taken into account, this will help to ensure optimum performance and lifetime of the LED system.

Optimum performance

The main thermal specification that needs to be taken into account when designing in LED module is the T_{case} temperature. The T_{case} must never exceed T_{case, lifetime test} in a draft-free lab environment. Please refer to the product datasheet for further details.



Warnings:

- Maximum T_{case} should never exceed specified T_{case max}
- Please refer to the specific datasheet for the maximum T_{case} Value
- Thermal design should ensure that driver T_{case} < max specified driver T_{case}
- Thermal design must ensure maximum ΔT (T_{case} - T_{amb}) ≤ 50 °C

Operating temperature

Definitions

Module temperature: temperature measured at the specified T_{case} point (at the base) of the module

Driver temperature: temperature measured at the specified T_{case} point on the driver

Ambient temperature: temperature of the air surrounding the luminaire in the test environment or application

Ambient temperature in a lab environment:

air temperature in a testing area, in a controlled environment free from drafts

Average ambient temperature: monthly average temperature based on at least 2 measurements per day, with at least 8-hour intervals between measurements

Module temperature

To achieve typical product lifetime characteristics, it is crucial to ensure that the product is operating within the specified temperature limits. These limits are determined not only by the product and the application, but also by the luminaire design and ambient environment.

Thermal measurements

The maximum ambient temperature at which the luminaire will operate constitutes the initial key criterion for defining the correct temperature limit and validating the thermal luminaire design.

Note:

The ambient temperatures given above are average temperatures during the operational period of the module

Critical temperature point (Tcase)


For LEDs, the junction temperature is the critical factor for operation. Since there is a direct relation between the case temperature and the LED junction temperature, it is sufficient to measure the aluminum casing of the module at its critical temperature point, Please refer to figure (Tc point on module). If the case temperature at the Tcase point exceeds the recommended Tcase lifetime, this will have an adverse effect on the performance of module in terms of light output, lifetime and lumen maintenance.

Measurement of critical temperature point


On the back of the module there is a Tcase (Tc) point, which should be used for all temperature measurements. The temperature must be stable before any reliable data can be obtained (depending on the size of the luminaire, this will take between 30 and 180 minutes and even overnight).

Note:

It is important that the Tcase point is free of thermal interface material when the thermocouple is connected so that temperature measurements can be taken. In order to ensure accurate Tcase test results, the case temperature should not vary by more than 1°C for a period of at least 30 minutes.



Electrical design-in and flexibility



Connection to the mains supply

The mains supply must be connected to the LED driver

Philips Xitanium outdoor driver

The CertaFlux Highbay modules are designed to be used with Philips Xitanium outdoor driver. This allows for an easier design-in for highbay luminaire design. More information about this driver family can be found in the Xitanium outdoor driver design in guide and commercial leaflet. These documents can be downloaded via

<http://www.lighting.philips.com.sg/oem-sg>


The Xitanium driver datasheets can also be downloaded on this website. Full system overviews can be obtained using the Easy Design-in tool at www.easydesignintool.philips.com.

Compatible Drivers

A list of compatible drivers, specific to your choice of module and operating point can be obtained from the Easy Design-in Tool that can be found at www.easydesignintool.com

In case of queries, please contact your Philips representative.

Reliability



Example

Lumen maintenance

B50L70 @ 30,000 hours

The quality of Philips module portfolio by the Philips' claim of B50L70 @ 30,000 hours. This means that at 30,000 hours of operation at least 50% of the module population will emit 70% of its original amount of lumens.

More detail regarding to lifetime, please find it in the commercial datasheet.

Controllability

Dimmable function offer this system

As a system, we recommend Philips Xitanium outdoor drivers for customer.

Philips Xitanium outdoor driver are specially designed for maximum reliability and core exhibity in outdoor applications. With superior surge protection, these durable, independently housed drivers deliver consistent, high performance to luminaires even after multiple indirect lightning strikes – an ideal solution for OEMs that need reliable, adjustable output in a rugged independent form factor.

Please refer to the driver design-in guide for more detailed information.

Further information about our entire portfolio of control products is available at:

www.Philips.com/lightingcontrols

Compliance and approval

Compliance and approbation

The relevant standards are summarized below. To ensure luminaire approval, the conditions of acceptance need to be fulfilled. Details can be requested from your local sales representative. All luminaire manufacturers are advised to conform to the international (luminaire standards IEC 60598-1) and national standards of luminaire design.

Electrostatic discharge (ESD)

ESD consultancy

Depending on the protection level of the LED module a minimum set of measures has to be taken when handling the modules. Philips LED products have a high degree of ESD protection by design. ESD measures are required in a production environment.

Environmental compliance

The product is compliant with European Directive 2011/65/EC on Restriction of the Use of Certain Hazardous Substances in electrical and electronic equipment (RoHS2).

Blue Light Hazard

The photobiological safety standard IEC TR 62778 ('Photobiological safety of lamps and lamp systems') gives guidance on how to evaluate the photobiological safety of lamps and lamp systems including luminaires. This standard specifies the exposure limits, reference measurement technique and classification scheme for the evaluation and control of photobiological hazards from all electrically powered incoherent broadband sources of optical radiation including LEDs in the wavelength range from 200 nm through 3000 nm. Measured results of emission limits for Philips modules using the non-GLS (20 cm) method are listed in the datasheets that can be found at <http://www.lighting.philips.com.sg/oem-sg>

From the nature of most LEDs applying blue light, emphasis has been put on the hazard in terms of Photo Biological Safety (PBS). Evaluation by the European lighting industry (ELC, Celma) has concluded LED light sources are safe for customers when used as intended. A photobiological safety report is available at <http://www.lighting.philips.com.sg/oem-sg>

Nevertheless luminaire makers have to comply with luminaire standards including PBS. To avoid extensive retesting, it is preferred to build on the test conclusions of the LED (module) suppliers; however this should be discussed and agreed upon with the used certification body. The testing conclusion then will be expressed in Risk Groups (RG), where RG0 and RG1 are considered safe and/or do not require specific action for the luminaire makers (as compared to RG2 and 3).

Chemical Name	Normally used as
Acetic acid	Acid
Hydrochloric acid	Acid
Nitric acid	Acid
Sulfuric acid	Acid
Ammonia	Alkali
Potassium hydroxide	Alkali
Sodium hydroxide	Alkali
Acetone	Solvent
Benzene	Solvent
Dichloromethane	Solvent
Gasoline	Solvent
MEK (Methyl Ethyl Ketone)	Solvent
MIBK (Methyl Isobutyl Ketone)	Solvent
Mineral spirits (turpentine)	Solvent
Tetrachlorometane	Solvent
Toluene	Solvent
Xylene	Solvent
Castor oil	Oil
Lard	Oil
Linseed oil	Oil
Petroleum	Oil
Silicone oil	Oil
Halogenated hydrocarbons (containing F,Cl,Br elements)	Misc
Rosin flux	Solder flux
Acrylic tape	Adhesive
Cyanoacrylate	Adhesive

Chemical Compatibility

The LED contains a silicone overcoat to protect the LED chip and extract the maximum amount of light. As with most silicones used in LED optics, care must be taken to prevent any incompatible chemicals from directly or indirectly reacting with the silicone.

The silicone overcoat used in the LED is gas sensitive. Consequently, oxygen and volatile organic compound (VOC) gas molecules can diffuse into it. VOCs may originate from adhesives, solder fluxes, conformal coating materials, potting materials and even some of the inks that are used to print the PCBs.

A list of commonly used chemicals, that should be avoided as they may react with the silicone material, is provided on the left. Note that Philips does not warrant that this list is exhaustive since it is impossible to determine all chemicals that may affect LED performance. These chemicals may not be directly used in the final products but some of them may be used in intermediate manufacturing steps (e.g. cleaning agents). Consequently, trace amounts of these chemicals may remain on (sub) components, such as heat sinks. It is recommended to take precautions when designing your application.

Cautions

During storage and transportation

Store in a dark place. Do not expose to sunlight. Maintain temperature between -40 +65 °C, and RH 5 – 95%.

During operation

Philips shall not be held responsible or liable for any damage, costs or expenses to the user, resulting from an accident or any other cause during operation if the system is used without due observance of the absolute maximum ratings and other instructions provided by Philips.

Note:

That warranty is applicable for Philips module for 1 switching cycle per day in combination with a released Philips Xitanium driver.

Contact details

Philips

www.Philips.com/Technology

Or contact your local Philips sales representative

Philips ESD support

www.innovationservices.philips.com

Phone : +31- (0) 40 27 46658

Fax : +31 – (0) 40 27 42224

The Philips corporate EMC competence center is a leading provider of approbation and consultancy services.

Disclaimer

Philips will perform the testing of the LED systems to high standards of workmanship. The tests are carried out with reference to the EN/IEC standards, if any, which are regarded by Philips as being of major importance for the application of the lamp gear and the lamp within the fixture for horticultural applications.

The design-in guide, regarding the testing and design in of the LED system provided by Philips, is not an official testing certificate, and cannot be regarded as a document for official release of the fixture. The OEM is liable for the official testing by a certified test body and all markings, such as CE and ENEC marks, on the fixture assembly.

The design-in guide is for information purposes only and may contain recommendations for detecting weak points in the design of the system (lamp – lamp gear – fixture), if any.

Specifically mentioned materials and/or tools from third parties are only indicative: other equivalent equipment may be used but it is recommended that you contact Philips for verification.

Philips will not be liable for unforeseen interactions of the proposed solutions when applied in the fixtures or applications using these fixtures. Philips has not investigated whether the recommendations are or will in the future be in conflict with existing patents or any other intellectual property right. Philips does not warrant that its recommendations are technically or commercially the best options.

Since the tests are only performed on one particular fixture provided by the customer, it will be treated as a prototype. This means that there is no statistical evidence regarding later production quality and performance of the lamp – lamp gear – fixture system.

As Philips does not have control over manufacturing of the fixtures, Philips cannot be held liable for the fixture assembly.

Philips will not accept claims for any damage caused by implementing the recommendations.

No warranty whatsoever may be claimed by the OEM with regard to the content and/or quality of the design-in guide or any other advice, or the conclusions and/or recommendations in the design-in guide or any other document, either express or implied, and Philips expressly disclaims any implied warranties of any kind, including without limitation any warranties of satisfactory quality, fitness for a particular purpose or non-infringement and any warranties regarding the design-in guide or any other advice or the use of the results of any activity performed while testing the fixture with respect to its correctness, quality, accuracy, completeness, reliability, performance or otherwise.

The OEM expressly agrees that test design-in guides are provided by Philips on an 'as is' basis and an 'as available' basis at customer's sole risk and expense. Philips shall not be liable for any lost profits or lost savings, indirect, incidental, punitive, special, or consequential damages whether or not such damages are based on tort, warranty, contract, or any other legal theory – even if Philips has been advised, or is aware, of the possibility of such damages.

The OEM must bring any claim for damages within ninety (90) days of the day of the event giving rise to any such claim, and all lawsuits relative to any such claim.



© 2018 Koninklijke Philips N.V.

All rights reserved. Reproduction in whole or in part is prohibited without the prior written consent of the copyright owner. The information presented in this document does not form part of any quotation or contract, is believed to be accurate and reliable and may be changed without notice. No liability will be accepted by the publisher for any consequence of its use. Publication thereof does not convey nor imply any license under patent or other industrial or intellectual property rights

<http://www.lighting.philips.com.sg/oem-sg>

13 March 2018
Data subject to change